

# Wiring Diagram for Salzer Reversing Drum Switch

For use with 3/4 hp, 1 hp, and 1.5 hp East Bay Motors

**GFCI Plug to Switch:**

**Plug Black to Switch 1**

**Plug White to Switch 3**

**( Wire-Nut Green to Switch Green )**

**Electric Cable from Motor to Switch:**

**Red to # 4**

**Black to # 8**

**Orange to # 12**

**White to # 2**

**( Wire-Nut Green to GFCI Green )**